

A 110 μ W 10Mb/s eTextiles Transceiver for Body Area Networks with Remote Battery Power

Patrick P. Mercier and Anantha P. Chandrakasan


Massachusetts Institute of Technology

ISSCC 2010



Vision: Personal Telehealth for Continuous Ambulatory Monitoring

- Opportunity for personal health monitoring to **reduce costs** and **improve quality of health care**
- Body-worn sensor nodes must be **light** & **unobtrusive**
- Use a **Body Area Network (BAN)** for sensor communication
 - Energy-rich local relay can communicate with cellular/ WiFi network



Move complexity away from the locations where size and weight are limited

1m BAN Communication Options

Option #	PROS	CONS
1. Wired	Low power, secure	Obtrusive, aesthetics
2. Wireless	Mobility	Battery life/size, security
3. Body-coupled communication (BCC)	Lower power than wireless, secure	Still much higher power than wired





Image from: [Cho, JSSC 09]
Other work: [Fazzi, ISSCC 09]


1m BAN Communication Using Electronic Textiles (eTextiles)

- PROS:
 - Secure
 - Ultra-low-power
 - Good aesthetics
- CONS:
 - Requires patients to wear specific clothing



**Secure, low-power communication
→ small sensor nodes with long battery life**

Implemented eTextiles System



Advantages of Two-Wire Interface

- **Differential signaling**

- Wireless and BCC are **inherently single-ended**; require signaling robustness against interferers
 - Higher-complexity modulation or avoidance techniques
- Wired differential communication can use simpler modulation (e.g. OOK) and be resilient to interferers

- **Remote charging**

- Greater than 95% power transfer efficiency over 1m (compared to $< 55\%$ for wireless over 1cm)
- Reduces energy storage requirements on size-constrained sensor nodes

**Significantly increased efficiency
of information and power transfer**

Networking Configuration


- Basestation (BS) eTextiles transceiver configured as master access point on **global (broadcast) medium**
 - Sensor nodes configured as **slave** devices with unique ID
- TDMA-based multi-access
 - **Ternary** (3-level) signaling eases packet detection
- Packet diagram:



 = BS TX; Node RX  = BS RX; Node TX  = No RX or TX


- “Request Packet” code can be a discovery code to dynamically accept new nodes to the network

eTextiles Transceiver Block Diagram




Supply-Rail-Coupled Differential Ternary Signaling

- Capacitive coupling onto rails that are floating at GND and V_{DD}
 - **Energy-efficient** low-swing signaling [Ho, ISSCC 07]




Transmitter Implementation

- Binary-weighted parallel tri-state inverters and coupling capacitors for programmable voltage swing




Receiver Front-End

- Ultra-low path loss → high SNR
→ **Direct supply-rail-coupled sampling @ 10Mb/s**





No static bias currents, only CV^2 energy

Acquisition (AQ) Front-End: Supply-Rail-Coupled Sampling & 1.5b ADC



Supply-Rail-Coupled Sampling (1): Purge & Preset



Purge Phase*: $\Phi_1=0$; $V_{sp} = V_{dd}$



$\Phi_2=0$; $V_{sn} = 0$

Preset Phase: $\Phi_1=0$; $V_{sp} = V_{dd}/2$

$\Phi_2=1$; $V_{sn} = V_{dd}/2$

***Purging only required
once per packet**

Supply-Rail-Coupled Sampling (2): Sample & Hold




Sample: $\Phi_1=1$; $V_{sp} = V_{DD}/2$
 $\Phi_2=1$; $V_{sn} = V_{DD}/2$
 $Q_{Cp} = -C_p(V_{DD}/2 + V_{in}/2 + V_{CMI})$
 $Q_{Cn} = C_n(V_{DD}/2 - V_{in}/2 + V_{CMI})$

Hold: $\Phi_1=0$; $V_{sp} = V_{DD}/2 - V_{in}/2 - V_{CMI}$
 $\Phi_2=0$; $V_{sn} = V_{DD}/2 + V_{in}/2 - V_{CMI}$

Common-mode-interference-independent sampling


1.5bit (Ternary) Flash-like ADC



Comparator output	$ V_{sp} - V_{sn} < off. $ (noise)	$V_{sp} - V_{sn} > off. $	$V_{sn} - V_{sp} > off. $
A (+offset)	0	0	1
B (-offset)	1	0	1
Trits output	'0'	'+1'	'-1'


Comparator Implementation

- Modified regenerative Strong-ARM-type latch
- 8b differential pair and current source DAC
 - Offset configurability of $\pm 60\text{mV}$ at $V_{DD} = 0.9\text{V}$




Measured Comparator-Configuration Redundancy Results

Offset Configurability




Calibration Statistics



Configuration redundancy improves the standard deviation of offset errors by 1.5-2.5X

Receiver Digital Back End: Synchronization


- Four interleaved front-end acquisition (AQ) blocks




Implemented eTextiles Chip

Chip Summary


Technology	0.18 μ m CMOS
Core area	0.83mm ²
V _{DD}	0.9V
Clock frequency	10MHz
Modulation	NRZ supply-rail-coupled differential ternary



Transient Measurement Results: Small TDMA Packet



Measured BER & Energy/Bit Performance



Summary	
TX voltage swing	6 - 290mV
TX front-end energy/bit	0.7 - 18pJ
RX front-end energy/bit	2pJ
RX 10^{-3} sensitivity	15mV
Range	1m

Comparable systems for ~1m BAN communications

	Verhelst ISSCC 2009	Cho ISSCC 2008	Yoo A-SSCC 2008	Yoo A-SSCC 2008	This Work
Type	UWB	BCC	Wireless eTextiles	Wired eTextiles	Wired eTextiles
RX FE E/bit	45pJ	225pJ	1.1pJ	*	2pJ
TX FE E/bit	*	70pJ	2.9pJ	*	0.7 – 18pJ
RX & BB Pwr	4.3mW	3.7mW	0.18mW	2.7mW	0.11mW
Range	10m	1.8m	0.01m	0.85m	1m
Data Rate	40Mb/s	10Mb/s	10Mb/s	10Mb/s	10Mb/s

**20-100X more efficient than wireless
or body-coupled communication**

Conclusions

- **Key goal**: move complexity away from the places where weight & volume (thus **energy**) are restricted
- Two-wire eTextiles system enables at least **20X more energy efficient** communication
 - Security & privacy benefits
- **Supply-rail-coupled** transmitting and sampling enables time-sharing of the medium between communication and remote powering
 - Remote power transfer with > 95% efficiency

Acknowledgements: FCRP C2S2, Intel Ph.D. Fellowship, NSERC Scholarship